



用束線帶束好(不可束太緊)
,再把多餘的束線帶剪掉

PIN ASSIGNMENT : (EVN)

Conn A :	1	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18
Conn B :	1	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18
Conn C :	1	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18
Conn A :	21	23	25	27	28	29	31	32	33	34	35	36	37	38	39		
Conn B :	21	23	25	27		29	31	32	33	34	35	36	37	38	39		
Conn C :	21	23	25	27	28	29	31	32	33		35	36	37	38	39		

GND :

- Conn A 2,19,22,24,26,30,40
- Conn B 2,19,22,24,26,30,40
- Conn C 2,19,22,24,26,30,34,40

BLACK	2	STRAIN RELIEF	7	HIB40-SR5
YELLOW	65 cm	ATAS CABLE	6	CFH80-P-065
BLACK	1	KNIT NET	5	XPL-114-170
BLACK	1	KNIT NET	4	XPL-114-410
BLUE	1	ATAS IDC	3	HIB40F-35P-15
GRAY	1	ATAS IDC	2	HIB40F-25P-15
BLACK	1	ATAS IDC	1	HIB40F-15P-15
REMARK	Q'TY	PART NAME	NO.	PART NO.

高位企業有限公司 Yes Way Enterprise Corp.		TOLERANCE UNSPECIFIED	
SCALE		UNIT	
1 : 1		mm	
NAME		SHEET	
ATA100 CABLE ASSEMBLY		1	
DRAWING NO.		REV	
A40A87-X060		1	
		DRAWN	
		Vivian 2/1/2002	
		DESIGNER	
		Reo	
		CHECKED	
		Jenny	
		APPROVED	
		Tim	
		A3	